



(12) **United States Patent**
Connell

(10) **Patent No.:** **US 10,077,916 B2**
(45) **Date of Patent:** **Sep. 18, 2018**

- (54) **PEST REPELLING DEVICE**
- (71) Applicant: **Plug In Pest Free Australia**, Wickham NSW (AU)
- (72) Inventor: **Raymond Connell**, Merewether Heights (AU)
- (73) Assignee: **ISpyTronics PTY LTD**, Wickham (AU)
- (*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 299 days.

- (56) **References Cited**
- U.S. PATENT DOCUMENTS
- 4,097,838 A 6/1978 Fiala
- 4,178,578 A 12/1979 Hall
- 4,215,429 A 7/1980 Riach
- 4,338,593 A 7/1982 Mills
- 4,414,653 A 11/1983 Pettinger
- 4,802,057 A 1/1989 Patterson et al.
- 4,870,779 A 10/1989 Johnson et al.
- 5,473,836 A 12/1995 Liu
- 5,930,946 A 8/1999 Mah
- 6,111,514 A 8/2000 Cossins et al.
- 6,208,100 B1 3/2001 Griesemer et al.
- 6,249,417 B1 6/2001 Pippen
- (Continued)

- (21) Appl. No.: **15/011,162**
- (22) Filed: **Jan. 29, 2016**

FOREIGN PATENT DOCUMENTS

- (65) **Prior Publication Data**
- US 2017/0219235 A1 Aug. 3, 2017

- AU 664508 11/1995
- AU 2009905046 10/2009
- (Continued)

Primary Examiner — Anthony Ho
(74) *Attorney, Agent, or Firm* — Craig Thompson;
Thompson Patent Law

- (51) **Int. Cl.**
- G05B 19/04** (2006.01)
- F24F 11/30** (2018.01)
- F24F 11/00** (2018.01)
- G05D 23/19** (2006.01)
- G05B 15/02** (2006.01)
- F24F 110/10** (2018.01)
- F24F 110/40** (2018.01)


(57) **ABSTRACT**

Apparatus and associated methods relate to a pest repelling magnetic field generating device (PRD) having a temperature sensor to detect the temperature of a solenoid coil during operation. The detected temperature to be used to ensure that the PRD operates within an ideal temperature range. Additionally, a fan is oriented within a housing of the PRD to force the flow of air from inside a housing of the PRD to outside a housing of the PRD. In an illustrative example, the PRD may shut off if the temperature of the solenoid coil moves outside the ideal temperature range. By operating the PRD within an ideal temperature range, the service life of the PRD may be extended. Further, the fan may mitigate dust collection within the housing of the pest repelling magnetic field generating device.

- (52) **U.S. Cl.**
- CPC **F24F 11/30** (2018.01); **F24F 11/0012** (2013.01); **G05B 15/02** (2013.01); **G05D 23/1927** (2013.01); **F24F 2011/0042** (2013.01); **F24F 2110/10** (2018.01); **F24F 2110/40** (2018.01)

- (58) **Field of Classification Search**
- CPC G05B 15/02; G05B 23/1927
- USPC 700/299
- See application file for complete search history.

16 Claims, 10 Drawing Sheets



(56)

References Cited

U.S. PATENT DOCUMENTS

6,400,995 B1 6/2002 Patterson et al.
2012/0263021 A1 10/2012 Connell

FOREIGN PATENT DOCUMENTS

AU 2015200650 2/2015
WO PCT/AU2010/001366 4/2011
WO WO-2011044635 A1 4/2011




FIG. 1




FIG.2A




FIG.2B




FIG. 2C




FIG.3A




FIG. 3B




FIG.4




FIG. 5




FIG. 6




FIG. 7

1

PEST REPELLING DEVICE**CROSS-REFERENCE TO RELATED APPLICATIONS**

This application contains subject matter related to U.S. patent application Ser. No. 13/502,034, entitled "Pest Repellent System and Device," filed Jul. 2, 2012 by Ray Connell, and Australian Patent Application Serial No. 2015200650, entitled "Improved Pest Repellent System and Device", filed Feb. 10, 2015 by Ray Connell.

This application incorporates the entire contents of the foregoing application(s) herein by reference.

TECHNICAL FIELD

Various embodiments relate generally to electro-magnetic devices for repelling pests.

SUMMARY

Apparatus and associated methods relate to a pest repelling magnetic field generating device (PRD) having a temperature sensor to detect the temperature of a solenoid coil during operation. The detected temperature to be used to ensure that the PRD operates within an ideal temperature range. Additionally, a fan is oriented within a housing of the PRD to force the flow of air from inside a housing of the PRD to outside a housing the PRD. In an illustrative example, the PRD may shut off if the temperature of the solenoid coil moves outside the ideal temperature range. By operating the PRD within an ideal temperature range, the service life of the PRD may be extended. Further, the fan may mitigate dust collection within the housing of the pest repelling magnetic field generating device.

Various embodiments may achieve one or more advantages. For example, some embodiments may include multiple temperature sensors to detect more accurate information concerning the temperature of the PRD. Various examples include a processor to operate the PRD according to different parameters, for example, time period parameters vs temperature parameters. In an another example, a user may control multiple PRD's via networked device, such as, for example, a mobile device.

The details of various embodiments are set forth in the accompanying drawings and the description below. Other features and advantages will be apparent from the description and drawings, and from the claims.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a schematic view of an exemplary multiple pest repellent devices (PRD) in operation in a pre-wired facility, and a user controlling the PRD's via a mobile device.

FIG. 2A is a perspective view of the outside of a housing of an exemplary PRD.

FIG. 2B is a perspective view of the inside of a housing of an exemplary PRD.

FIG. 2C is a perspective view of the components of an exemplary PRD.

FIG. 3A is a cross-section view of an exemplary solenoid coil with a singular temperature sensor.

FIG. 3B is a cross-section view of an exemplary solenoid coil with multiple temperature sensors.

FIG. 4 is a graph of periods of operation for an exemplary PRD.

2

FIG. 5 is a schematic diagram of an exemplary embodiment of a PRD circuit.

FIG. 6 is a flow chart diagram of an exemplary pest repelling operation.

FIG. 7 is a flow chart diagram of an exemplary profile selection subroutine.

Like reference symbols in the various drawings indicate like elements.

DETAILED DESCRIPTION OF ILLUSTRATIVE EMBODIMENTS

FIG. 1 is a schematic view of an exemplary multiple pest repellent devices (PRD) in operation in a pre-wired facility, and a user controlling the PRD's via a mobile device. An AC power line 105 connects to an external power connector 110 of a facility 100. Wires 115 are located throughout the facility 100 and connect to the external power connector 110 to distribute power throughout the facility 100. The wires 115 having power outlets 135 located throughout the facility. As depicted, each PRD 120a, 120b connects to different power outlets 135. Each PRD 120a, 120b includes a coil (described in further detail in FIGS. 2A-2C), a temperature sensor (described in further detail in FIGS. 3A-3B), a fan (described in further detail in FIGS. 2A-2C), and a processor to operate the PRD (described in further detail in FIG. 5). The temperature sensor detects the temperature information of the coil and transmits the temperature information to the processor. The processor uses the transmitted temperature information to determine whether or not to permit current flow through the coil. By only permitting current to flow through the coil at ideal operating temperatures of the coil, the service life of the PRD 120a, 120b is extended. As such, the fan also extends the service life of the PRD 120a, 120b by causing air to flow from an inside of the PRD 120a, 120b to an outside of the PRD 120a, 120b. The direction of the air flow mitigates dust build-up in the PRD 120a, 120b.

When in operation, each PRD 120a, 120b modulates a magnetic field 125 that radiates in all directions from the PRD's 120a, 120b. The wires 115 further serve as a path for the PRD's 120a, 120b to transmit, along the wires, the magnetic field 130. In various embodiments, the PRD 120a, 120b may advantageously modulate the magnetic field 125 in a manner effective to repel pests from the facility 100.

As depicted, a user 150 operates a mobile device 145. The mobile device 145 is in two-way communication with a network 140. The network 140 is further in two-way communication with the PRD 120a located in the facility 100. In an exemplary embodiment, the user 150 may receive status information about the operation of the PRD's 120. In response to the received status information, the user 150 may send operation instructions to the PRD's 120a.

In some embodiments, the user 150 may send operation instructions that include individual shutoff commands for each PRD 120a, 120b. For example, in a situation where the user 150 may be away from the facility 100 for an extended period of time, the user 150 may receive status information for one PRD 120a showing the temperature of the coil above a predetermined ideal operating temperature. The user may receive status information for the other PRD 120b showing the temperature of the coil within a predetermined ideal operating temperature. In response to the received signals, the user 150 may issue a shutdown command for the PRD 120a while continuing operation of the PRD 120b. In some embodiments, the status information about the PRD 120a,

120b may include other information besides temperature of the coil, for example, time in operation for the PRD **120a**, **120b**.

FIG. 2A is a perspective view of the outside of a housing of an exemplary PRD. In the depicted figure, the PRD housing **200** is rectangular in shape having a profile similar to that of a right trapezoid. The housing **200** may be constructed of sheet metal. As such, two opposing parallel walls of the housing have different heights, one wall having a greater height and the opposing wall having a lesser height. The housing **200** includes an upper portion **205** and a lower portion **210**. The upper portion **205** includes three apertures **230a-230c**. As depicted, the apertures **230a-230c** are located on the upper portion **205** near the wall of lesser height. The three apertures **230a-230b** may each receive a light indicator to indicate the status of the PRD **120a**, **120b**. For example, the aperture **230b** may receive a light indicator to indicate the power status of the PRD **120**. If the PRD **120** is receiving power, the light indicator at aperture **230b** may light on. The aperture **230a** and **230c** may receive light indicators to display the operation state of the PRD **120a**, **120b**. For example, a light indicator at aperture **230a** may activate to indicate that the PRD **120a**, **120b** is in a standby mode. A light indicator at aperture **230c** may activate to indicate that the PRD **120a**, **120b** is in an oscillation mode. In some embodiments, the light indicators at apertures **230a-230c** may activate individually or in conjunction to indicate different operating states.

The lower portion **210** includes, on a side wall between the parallel walls, a group of apertures **225** arranged to form a circular pattern. The lower portion **210**, along the wall of greater height, has two apertures. The first aperture receives a power connector **215**. The second aperture receives a fuse **220** such that the fuse **220** is accessible from the outside of the housing **200**. In some embodiments, the fuse **200** may be located at different locations of the housing **200** for increased accessibility to the fuse **200** in relation to the placement of the PRD. In some embodiments, the housing **200** may be composed of sheet metal. In other embodiments, the housing **200** may be composed of a plastic material.

FIG. 2B is a perspective view of the inside of a housing of an exemplary PRD. As depicted, a construction of the PRD **120a**, **120b** is illustrated without the upper portion **205** of the housing **200**. A three-sided U-shaped coil support frame **235** includes two parallel side walls, and a singular wall connecting the two parallel side walls. The U-shaped coil support frame **235** may be constructed of sheet metal. The U-shaped coil support frame **235** attaches, at the open end of the parallel walls to the lower portion **210** of the housing **200**. A solenoid coil **240** attaches to the parallel side walls of the U-shaped coil support frame **235**. In some embodiments, multiple solenoid coils may be attached inside the U-shaped coil support frame. A spring may be placed between the multiple coils to prevent the multiple coils from touching.

A circuit board **250** attaches to lower portion **205** of the housing **200**. The circuit board **250** includes a circuit for operating the PRD **120a**, **120b** including a processor **255** to receive information and generate operation commands. Three indicator lights **245a-245c** for indicating status information about the operation state of the PRD **120a**, **120b** attach to the circuit board **250**. In some embodiments, the number of indicator lights **245a-245c** may be increased or decreased.

A fan **260** attaches to a side wall of the lower portion **210** in alignment with the group of apertures **225**. In various

embodiments, multiple groups of apertures may be distributed around the housing **200** to align with multiple fans.

FIG. 2C is a perspective view of the components of an exemplary PRD. As depicted, the upper portion **205** of the housing **200** is located above the lower portion **210**. The upper portion **205** includes the apertures **230a-230c** aligned to receive the indicator lights **245a-245c**. The indicator lights **245a-245c** attach to the circuit board **250**. The circuit board **250** is between the upper portion **205** and the lower portion **210**. The U-shaped coil support frame **235** above the lower portion **210** and below the upper portion with the solenoid coil **230** to a side of the U-shaped coil support frame. As depicted, the fuse **220** and the power connector **215** are behind and beside the lower portion **210**. Below the lower portion **210**, four rest pedestals are depicted. The pedestals may raise up the housing **200** to provide an air space thereunder. In some embodiments, intake apertures may be formed in a bottom the housing **200**. The intake apertures may advantageously provide an air flow intake path for air to be drawn to cool the PRD components, such as the solenoid coil **240**, in response to the action of the exhaust fan **260**. The intake apertures may be provided, in some examples, along the seams of the housing **200** where the top meets the base portions of the housing **200**, for example. Filter screens may be used to substantially mitigate the ingress of dust, for example.

FIG. 3A is a cross-section view of an exemplary solenoid coil with a singular temperature sensor. The solenoid coil **300** includes an axle **305**. The axle **305** runs through the center of the wiring **310** of solenoid coil **300**. As depicted, the axle **305** connects to ground **330**. The wiring **310** of the solenoid coil **300** includes two terminal connections **315** **320**. The two terminals **315** **320** may connect the solenoid coil to other electrical components. For example, the terminal connector **315** may connect to a power source and the terminal connector **320** may connect to an activation switch. In some embodiments, the activation switch may be a triac. A temperature sensor **325** is located in the longitudinal center of the solenoid coil **300**.

FIG. 3B is a cross-section view of an exemplary solenoid coil with multiple temperature sensors. As depicted, the axle **305** runs through the center of the wiring **310** of the solenoid coil **300**. The temperature sensor **325** remains located in the longitudinal center of the solenoid coil **300**. A second temperature sensor **340** is located above a left side of the solenoid coil **300**. A third temperature sensor **335** is located below a right side of the solenoid coil **300**. Each of the temperature sensors **325**, **335**, **340** may transmit temperature information about the solenoid coil **300** relative to the location of each temperature sensor **325**, **335**, **340**. As such, more accurate temperature information concerning the temperature of the solenoid coil may be collected to improve the operation efficiency of the PRD **120**.

In some embodiments, a combination of the temperature sensors **325**, **335**, **340** may be used. For example, the temperature sensor **325** may be used in conjunction with the second temperature **340**, or the second **340** and third temperature sensor **335** may be used in conjunction and without the temperature sensor **325**.

FIG. 4 is a graph of periods of operation for an exemplary PRD. As depicted, the vertical axis represents the values for a triac that controls the current flow through the solenoid coil **300**. The triac has a deactivation period **415** when the triac has a value of zero **410**. The triac has an activation period **420** when the triac has a value of one **405**. A periodic cycle **440** includes a deactivation period **415** and an activation period **420**. The periodic cycle **440** may have a length of 4.8

seconds. The deactivation period **415** and the activation period **420** may be of equal length, for example, both the deactivation period and the activation periods may have a length of 2.4 seconds. During the deactivation period **415**, the triac prevents current from flowing through the solenoid coil **300**.

During the activation period **420**, the triac permits current to flow through the solenoid coil in burst cycles **425**. The burst cycles **425** are smaller periods within the activation period **420**. Each burst cycle **425** includes a current flow period **430** and a current no-flow period **435**. During the current flow period **430**, the triac permits current to flow through the solenoid coil **300**. During the current no-flow period **435**, the triac does not permit current to flow through the solenoid coil **300**. The current flow period **430** and the current no-flow period **435** may be equal in length. These burst cycles **425** create a pulsating effect during the activation period **420**. The activation period **420** may include many burst cycles **425**, for example, 225 burst cycles may be included in one activation period.

In some embodiments, the deactivation period **415** and the activation period **420** may be of different lengths. In other embodiments, the current flow period **430** and the current no-flow period **435** may be equal in length.

In some embodiments, the deactivation period **415** and the activation period **420** may not be dependent on the length of time, for example, the deactivation **415** and activation **420** period may be dependent on the temperature of the solenoid coil **300**. A predetermined threshold for a high temperature for the solenoid **300** may be set, such that, when the temperature of the solenoid coil **300** exceeds the predetermined high-temperature threshold, the PRD **300** may enter the deactivation period **415**. A predetermined threshold for a low temperature for the solenoid coil **300** may be set, such that, when the temperature of the solenoid coil **300** exceeds the predetermined low temperature, the PRD **300** may enter the activation period. The activation period may last as long as the temperature of the solenoid coil **300** does not exceed predetermined high temperature.

FIG. 5 is a schematic diagram of an exemplary embodiment of a PRD circuit. A semiconductor switching device **510** connects in series to an iron core coil **515** between a hot and neutral line of the AC line **505**. The iron core coil **515** is disposed within a filter control **520**. A temperature sensor **525** detects temperature information for the iron core coil **515** and transmits the detected temperature information to a central processing unit (CPU) **535**. The CPU **535** has a random access memory module (RAM) **540**, a non-volatile memory module (NVM) **545**, a user interface module (UI) **550**, a communications port module (Comm) **560**, and a processor **570**.

The CPU **535**, in response to receiving the detected temperature information, triggers the processor **570** execute a pest repelling operation (described in further detail in FIG. 6). The pest repelling operation involves the processor **570** executing a health check of the PRD by comparing the detected temperature information against a predetermined ideal operation temperature range contained in the NVM **545**. For example, if the detected temperature exceeds the predetermined ideal range, the processor **570** may communicate with the NVM **545** to generate a shutdown command to a switch controller **555**. The switch controller **555** executes the shutdown command by deactivating the semiconductor switching device to prevent current from flowing through the iron core coil **515** effecting a current blocking state. In another example, if the detected temperature does exceed the predetermined ideal range, the processor **570**

may generate a turn-on command to a switch controller **555** for activating the semiconductor switching device **510** to modulate a conductivity through the iron core coil **515** effecting a current flow state.

The CPU **535** may receive user input data from a serial port (RS232) connect to the Comm **560** or from a human machine interface (HMI) **575**. The processor **570** may execute the user input data to select a burst profile (described in further detail in FIG. 7) according to the user input data. For example, if the user input data calls for a modification to a burst cycle **425** during the activation period **420**, the processor may communicate with the NVM **545** to generate a burst profile to the switch controller **555**. The switch controller **555** will activate and deactivate the semiconductor switch **510** between current blocking states and current flow states according to the burst profile.

A display **590** is connected to the UI **550** for displaying information about the operation of the PRD to a user.

A zero cross detector **580** connects to the hot and neutral lines of the AC line **505** to operate in conjunction with a phase shifter (PS) **585** to generate a phase shift control signal to the CPU **535**. Upon receiving the phase shift control signal, the processor **570** may use the phase shift control signal to generate a burst profile, in accordance with the phase shift control signal, to the switch controller **555**.

FIG. 6 is a flow chart diagram of an exemplary pest repelling operation. At step **610**, the processor performs a self-healthcare check to generate a health message, at step **615**, to a communications port. At **620**, if the health message is negative, the processor, at step **625**, checks to see if the temperature of the coil exceeds a predetermined threshold. If the temperature does exceed a predetermined threshold, the processor, at step **630**, sets a timer to turn off the PRD. At step **635**, an expiration check is conducted to determine if the timer has expired. If the timer has not expired, the expiration check will repeat itself until the timer is expired. Once the expiration check determines the timer has expired, the processor will perform a self-health check at step **610**.

If, at step **625**, the temperature of the coil does not exceed the predetermined threshold, then, at step **640**, the fan turns on to exhaust air from the housing of the PRD. At step **645**, the processor receives a burst profile for the operation of the PRD (described in further detail in FIG. 7). Using the burst profile, at step **650**, an activate sequence is initiated for an activation period generating control signals, at step **655**, in accordance with per switch control timing parameters, to begin the burst by activating the switch to permit current to flow through a solenoid coil. At step **660**, the processor determines, according to the burst profile from step **645**, if it is time to end the burst by deactivating the switch. If it is not time end the burst, the processor will further generate control signals, at step **655**. If it is time to end the burst, at step **665**, the processor will determine whether or not to begin a next burst. In the event of a next burst, the processor repeats steps **650-665**. If no next burst is called for at step **665**, the processor will decide if it is time to deactivate the PRD. In the event it is not time to deactivate the PRD, step **665** repeats. In the event it is time to activate the PRD, the processor, at step **675**, will determine if it is time to activate the PRD. If it is time to activate the PRD, the processor will begin the process again, at step **610**. If it is not time to activate the PRD, the processor will determine, according to the burst profile received at step **645**, whether or not the pest repelling operation is complete. If the pest repelling operation is not complete, step **675** repeats. If the pest repelling operation is complete, the operation ends.

FIG. 7 is a flow chart diagram of an exemplary profile selection subroutine. FIG. 7 depicts the subroutine for step 645. At step 705, the processor determines whether user input will be required. A negative response at step 705 will cause the processor to determine if a dynamic selection will be used. If a dynamic selection is required, whether or not the PRD needs to be synchronized with other PRD's is determined, at step 720. In the event that the PRD needs to be synchronized with other PRD's, at step 725, synchronized information is retrieved from synched PRD's. At step 730, a next profile is selected according to the information received from step 725. The next profile will then be retrieved, at step 750, from a data store. The next profile is then transmitted to step 650.

In the event that the PRD does not need to synchronize with other PRD devices, at step 720, a next profile will be automatically selected based on predetermined selection criteria, at step 735. The selected next profile will then be retrieved, at step 750, from a data store. The next profile is then transmitted to step 650.

In the event that no dynamic selection is required, at step 710, a next profile will be set to a default profile, at step 715. The next profile will then be retrieved, at step 750, from a data store. The next profile is then transmitted to step 650.

If, at step 705, it is determined that user input is required, a user will be prompted to select a profile, at step 740. The user input will be received, at step 745, to select the next profile. The next profile will then be retrieved, at step 750, from a data store. The next profile is then transmitted to step 650.

Although various embodiments have been described with reference to the Figures, other embodiments are possible. For example, the communications port 560 may include wireless network module to enable communication between a PRD and a mobile wireless device. The wireless communication may be peer-to-peer or via a wide area network. In other embodiments, a user may input operation commands via a mechanical user input located on the device.

In some embodiments, AC phase control may be employed by the processor as a method of operating the solenoid coil by not firing the triac until the AC line voltage reaches a desired phase angle. By delaying trigger signal to the triac, the processor can effectively control the current waveform amplitude, and thereby the strength of the generated magnetic field weakens. This may advantageously be used to manage the temperature of the solenoid coil, for example, on days when the ambient temperature is high. By reducing the amplitude of the current, less heat will be generated by the current, and the pest repellent operation may be maintained at a reduced magnetic field in the event of high ambient temperature.

In other embodiments, the switch may be a bidirectional switch. The processor may be a single core processor or multi-core processor. Suitable processors for the execution of a program of instructions include, by way of example and not limitation, both general and special purpose microprocessors, which may include a single processor or one of multiple processors of any kind of computer. Generally, a processor will receive instructions and data from a read-only memory or a random access memory or both. The essential elements of a computer are a processor for executing instructions and one or more memories for storing instructions and data. Storage devices suitable for tangibly embodying computer program instructions and data include all forms of non-volatile memory, including, by way of example, semiconductor memory devices, such as EPROM, EEPROM, and flash memory devices; magnetic disks, such

as internal hard disks and removable disks; magneto-optical disks; and, CD-ROM and DVD-ROM disks. The processor and the memory can be supplemented by, or incorporated in, ASICs (application-specific integrated circuits). In some embodiments, the processor and the member can be supplemented by, or incorporated in hardware programmable devices, such as FPGAs, for example.

In other embodiments, a centralized database may contain identification information, for example, serial numbers, about each PRD distributed throughout a facility. The PRD's may transmit operation information, for example, the temperature of a solenoid coil to be saved in the centralized database. A centralized location, for example, a company offering monitoring services, may access the database to monitor operation information for individual PRD's to ensure proper functioning of an individual PRD. For example, the company may be alerted when an individual PRD operation nears a predetermined high threshold temperature. As such, the company may proactively monitor the individual PRD to ensure that the individual PRD shuts down if the predetermined high threshold temperature is exceeded. In the event the PRD does not shut down if the high threshold temperature is exceeded, the company may respond more quickly to addressing the issue. In some embodiments, the centralized database may collect information from PRD's across multiple facilities.

A number of implementations have been described. Nevertheless, it will be understood that various modifications may be made. For example, advantageous results may be achieved if the steps of the disclosed techniques were performed in a different sequence, or if components of the disclosed systems were combined in a different manner, or if the components were supplemented with other components. Accordingly, other implementations are contemplated.

What is claimed is:

1. A pest repelling magnetic field generating device comprising:

- a housing including at least one aperture;
- a fan coupled to the housing, wherein the fan is oriented to force air to flow through the at least one aperture from an inside of the housing to an outside of the housing;
- a solenoid coil disposed in the housing and having a first winding terminal configured to connect to a first power terminal of a power source;
- a semiconductor switching device having a control terminal, and a first and a second current carrying terminals, wherein a conductivity between the first and second current carrying terminals is modulated in response to a control signal applied to the control terminal, wherein the first current carrying terminal connects to a second winding terminal of the solenoid coil, and the second current carrying terminal connects to a second power terminal of the power source;
- a temperature sensor configured to sense a temperature of the solenoid coil;
- a processor operably coupled to the temperature sensor and the control terminal of the semiconductor switching device;
- a non-volatile memory operably coupled to the processor, the non-volatile memory including a program of instructions that, when executed by the processor, cause the processor to perform operations to operate the solenoid coil, the operations comprising:
 - receive, from the temperature sensor, temperature information about the solenoid coil;

determine whether the received temperature information meets a predetermined threshold as defined by the program of instructions;

if the received temperature information does not exceed the predetermined threshold, transmit a control signal to the control terminal of the semiconductor switching device to modulate the conductivity between the first and second current carrying terminals of the semiconductor switching device according to a predetermined burst profile in the program of instructions; and,

if the received temperature information does exceed the predetermined threshold, disable the semiconductor switching device to effect a current blocking state between the first and second current carrying terminals of the semiconductor switching device.

2. The pest repelling magnetic field generating device of claim 1, wherein the predetermined burst profile comprises a plurality of periodic cycles, each periodic cycle of the plurality of periodic cycles having a deactivation period and an activation period.

3. The pest repelling magnetic field generating device of claim 2, wherein the processor disables the semiconductor switching device to effect a current blocking state between the first and second current carrying terminal during each deactivation period.

4. The pest repelling magnetic field generating device of claim 3, wherein the deactivation period is approximately 2.4 seconds.

5. The pest repelling magnetic field generating device of claim 2, wherein during each activation period, the processor alternatively modulates the conductivity and disables the semiconductor switching device to effect a current blocking state, between the first and second current carrying terminals of the semiconductor switching device.

6. The pest repelling magnetic field generating device of claim 5, wherein the activation period is approximately 2.4 seconds.

7. The pest repelling magnetic field generating device of claim 1, wherein modulating further comprises phase controlling the control signal for the semiconductor switching device relative to a phase of an excitation signal at the first and the second power terminals of the power source.

8. The pest repelling magnetic field generating device of claim 1, further comprising a fuse accessible from outside of the housing, the fuse having a first fuse terminal and a second fuse terminal, wherein the first fuse terminal connects to one of the power source terminals and the second fuse terminal connects to one of the winding terminals.

9. The pest repelling magnetic field generating device of claim 1, further comprising a communication module operably coupled to the processor and configured to receive instructions for modification of the burst profile.

10. A method of generating a pest repelling magnetic field comprising:

providing a housing including at least one aperture; operating a fan coupled to the housing, wherein the fan is oriented to force air to flow through the at least one aperture from an inside of the housing to an outside of the housing;

disposing a solenoid coil in the housing, the solenoid coil having a first winding terminal configured to connect to a first power terminal of a power source;

providing a semiconductor switching device having a control terminal, and a first and a second current carrying terminals;

modulating, in response to a control signal, a conductivity between the first and second current carrying terminals, wherein the first current carrying terminal connects to a second winding terminal of the solenoid coil, and the second current carrying terminal connects to a second power terminal of the power source;

sensing with a temperature sensor a temperature of the solenoid coil;

providing a processor operably coupled to the temperature sensor and the control terminal of the semiconductor switching device;

providing a non-volatile memory operably coupled to the processor, the non-volatile memory including a program of instructions that, when executed by the processor, cause the processor to perform operations to operate the solenoid coil, the operations comprising:

receiving, from the temperature sensor, temperature information about the solenoid coil;

determining whether the received temperature information meets a predetermined threshold as defined by the program of instructions;

if the received temperature information does not exceed the predetermined threshold, transmitting a control signal to the control terminal of the semiconductor switching device to modulate the conductivity between the first and second current carrying terminals of the semiconductor switching device according to a predetermined burst profile in the program of instructions; and,

if the received temperature information does exceed the predetermined threshold, disabling the semiconductor switching device to effect a current blocking state between the first and second current carrying terminals of the semiconductor switching device.

11. The method of generating a pest repelling magnetic field of claim 10, wherein the predetermined burst profile comprises a plurality of periodic cycles, each periodic cycle of the plurality of periodic cycles having a deactivation period and an activation period.

12. The method of generating a pest repelling magnetic field of claim 11, wherein the processor disables the semiconductor switching device to effect a current blocking state between the first and second current carrying terminal during each deactivation period.

13. The method of generating a pest repelling magnetic field of claim 12, wherein the deactivation period is approximately 2.4 seconds.

14. The method of generating a pest repelling magnetic field of claim 11, wherein during each activation period, the processor alternatively modulates the conductivity and disables the semiconductor switching device to effect a current blocking state, between the first and second current carrying terminals of the semiconductor switching device.

15. The method of generating a pest repelling magnetic field of claim 14, wherein the activation period is approximately 2.4 seconds.

16. The method of generating a pest repelling magnetic field of claim 10, wherein modulating further comprises phase controlling the control signal for the semiconductor switching device relative to a phase of an excitation signal at the first and the second power terminals of the power source.